

ANSI escape code

ANSI escape sequences are a standard for in-band signaling to control the cursor location, color, and other options on video text terminals and terminal emulators. Certain sequences of bytes, most starting with Esc and '[', are embedded into the text, which the terminal looks for and interprets as commands, not as character codes.

ANSI sequences were introduced in the 1970s to replace vendor-specific sequences and became widespread in the computer equipment market by the early 1980s. They were used in development, scientific and commercial applications and later by the nascent bulletin board systems to offer improved displays compared to earlier systems lacking cursor movement, a primary reason they became a standard adopted by all manufacturers.

Although hardware text terminals have become increasingly rare in the 21st century, the relevance of the ANSI standard persists because most terminal emulators interpret at least some of the ANSI escape sequences in output text. A notable exception was DOS and older versions of the Win32 console of Microsoft Windows.

Contents

History

Platform support

- Unix-like systems
- DOS
- OS/2
- Atari ST
- AmigaOS
- Windows

Escape sequences

CSI sequences

SGR (Select Graphic Rendition) parameters

Colors

- 3/4 bit
- 8-bit
- 24-bit

Examples

- Example of use in shell scripting

Invalid and ambiguous sequences in use

See also

Notes

References

External links

History

Almost all manufacturers of video terminals added vendor-specific escape sequences to perform operations such as placing the cursor at arbitrary positions on the screen. One example is the VT52 terminal, which allowed the cursor to be placed at an *x,y* location on the screen by sending the ESC character, a *y* character, and then two characters representing with numerical values equal to the *x,y* location plus 32 (thus starting at the ASCII space character and avoiding the control characters).

As these sequences were different for different terminals, elaborate libraries such as termcap and utilities such as tput had to be created so programs could use the same API to work with any terminal. In addition many of these terminals required sending numbers (such as row and column) as the binary values of the characters; for some programming languages, and for systems that did not use ASCII internally, it was often difficult or impossible to turn a number into the correct character.

The ANSI standard attempted to address these problems by making a command set that all terminals would use and requiring all numeric information to be transmitted as ASCII numbers. The first standard in the series was ECMA-48, adopted in 1976. It was a continuation of a series of character coding standards, the first one being ECMA-6 from 1965, a 7-bit standard from which ISO 646 originates. The name "ANSI escape sequence" dates from 1979 when ANSI adopted ANSI X3.64. The ANSI X3L2 committee collaborated with the ECMA committee TC 1 to produce nearly identical standards. These two standards were merged into an international standard, ISO 6429.^[1] In 1994, ANSI withdrew its standard in favor of the international standard.

The first popular video terminal to support these sequences was the Digital VT100, introduced in 1978.^[2] This model was very successful in the market, which sparked a variety of VT100 clones, among the earliest and most popular of which was the much more affordable Zenith Z-19 in 1979.^[3] Others included the Qume QVT-108, Televideo TVI-970, Wyse WY-99GT as well as optional "VT100" or "VT103" or "ANSI" modes with varying degrees of compatibility on many other brands. The popularity of these gradually led to more and more software (especially bulletin board systems and other online services) assuming the escape sequences worked, leading to almost all new terminals and emulator programs supporting them.

In 1981, ANSI X3.64 was adopted for use in the US government by FIPS publication 86. Later, the US government stopped duplicating industry standards, so FIPS pub. 86 was withdrawn.^[4]

ECMA-48 has been updated several times and is currently at its 5th edition, from 1991. It is also adopted by ISO and IEC as standard **ISO/IEC 6429**.

Platform support

Unix-like systems

Although termcap/terminfo-style libraries were primarily developed on and for Unix, since about 1984 programs running on Unix-like operating systems could almost always assume they were using a terminal or emulator that supported ANSI sequences; this led to widespread use of ANSI by programs running on those platforms. For instance, many games and shell scripts (see below for colored prompt examples), and utilities such as color directory listings, directly write the ANSI sequences and thus cannot be used on a terminal that does not interpret them. Many programs, including text editors such as vi and GNU Emacs, still use termcap or terminfo, or use libraries such as curses that use termcap or terminfo, and thus in theory support non-ANSI terminals, but this is so rarely tested nowadays that they are unlikely to work with those terminals. Terminal emulators for communicating with local programs as well as remote machines and the text system console almost always support ANSI escape codes.

DOS

MS-DOS 1.x did not support the ANSI or any other escape sequences. Only a few control characters (BEL, CR, LF, BS) were interpreted by the underlying BIOS, making it almost^[nb 1] impossible to do any kind of full-screen application. Any display effects had to be done with BIOS calls, which were notoriously slow, or by directly manipulating the IBM PC hardware.

DOS 2.0 introduced the ability to add a device driver for the ANSI escape sequences – the *de facto* standard being ANSI.SYS, but others like ANSI.COM,^[5] NANSI.SYS^[6] and ANSIPLUS.EXE are used as well (these are considerably faster as they bypass the BIOS). Slowness and the fact that it was not installed by default made software rarely take advantage of it; instead, applications continued to directly manipulate the hardware to get the text display needed. ANSI.SYS and similar drivers continued to work in Windows 9x up to Windows Me, and in NT-derived systems for 16-bit legacy programs executing under the NTVDM.

PTS-DOS^{[7][8]} as well as Concurrent DOS, Multuser DOS^[9] and REAL/32 have built-in support for ANSI escape sequences (plus a number of extensions) and do not require a separate ANSI driver to be loaded.

OS/2

The ANSI command in a batch file or at the command line enables the extensions.

Atari ST

The Atari ST used the command system adapted from the VT52 with some expansions for color support,^[10] rather than supporting ANSI escape codes.

AmigaOS

AmigaOS not only interprets ANSI code sequences for text output to the screen, the AmigaOS printer driver also interprets them (with extensions proprietary to AmigaOS) and translates them into the codes required for the particular printer that is actually attached.^[11]

Windows

The Win32 console did not support ANSI escape sequences at all. Some replacements or additions for the console window such as JP Software's TCC (formerly 4NT), Michael J. Mefford's ANSI.COM, Jason Hood's ANSICON^[12] and Maximus5's ConEmu interpreted ANSI escape sequences printed by programs. A Python package^[13] internally interpreted ANSI escape sequences in text being printed, translating them to calls to manipulate the color and cursor position, to make it easier to port Python code using ANSI to Windows.

In 2016 with Windows 10 Version 1511, codenamed Threshold 2 Microsoft unexpectedly started supporting ANSI escape sequences^[14] in the console app, making the porting of software from (or remote access to) Unix much easier. This is not the default behavior; a program must turn it on with `SetConsoleMode(handle, ENABLE_VIRTUAL_TERMINAL_PROCESSING)`.^[15] This was enabled by CMD.EXE but not initially by PowerShell^[16] however Windows PowerShell 5.1 now enables this by default. The ability to make a string constant containing ESC was added in PowerShell 6 with (for example) `"`e [32m"`,^[17] for PowerShell 5 you had to use `[char]0x1b+" [32m"`.

Escape sequences

Sequences have different lengths. All sequences start with ESC (27 / hex 0x1B / octal 033), followed by a second byte in the range 0x40–0x5F (ASCII @A–Z[\]^_).^{[18]:5-3-a}

The standard says that in 8-bit environments these two-byte sequences can be merged into single C1 control code in the 0x80–0x9F range.^{[18]:5-4-a} However on modern devices those codes are often used for other purposes, such as parts of UTF-8 or for CP-1252 characters, so only the 2-byte sequence is used.

Other Co codes besides ESC — commonly BEL, BS, CR, LF, FF, TAB, VT, SO, and SI — produce similar or identical effects to some control sequences when output.

Some ANSI escape sequences (not a complete list)

Sequence	C1	Name	Effect
ESC N	0x8e	SS2 – Single Shift Two	Select a single character from one of the alternative character sets. In xterm, SS2 selects the G2 character set, and SS3 selects the G3 character set. ^[19]
ESC O	0x8f	SS3 – Single Shift Three	
ESC P	0x90	DCS – Device Control String	Terminated by ST. Xterm's uses of this sequence include defining User-Defined Keys, and requesting or setting Termcap/Terminfo data. ^[19]
ESC [0x9b	CSI - Control Sequence Introducer	Most of the useful sequences, see next section.
ESC \	0x9c	ST – String Terminator	Terminates strings in other controls. ^{[18]:8.3.143}
ESC]	0x9d	OSC – Operating System Command	Starts a control string for the operating system to use, terminated by ST. ^{[18]:8.3.89} In xterm, they may also be terminated by BEL. ^[19] In xterm, the window title can be set by OSC 0; this is the window title BEL.
ESC X	0x98	SOS – Start of String	Takes an argument of a string of text, terminated by ST. The uses for these string control sequences are defined by the application ^{[18]:8.3.2,8.3.128} or privacy discipline. ^{[18]:8.3.94} These functions are not implemented and the arguments are ignored by xterm. ^[19]
ESC ^	0x9e	PM – Privacy Message	
ESC _	0x9f	APC – Application Program Command	
ESC c		RIS – Reset to Initial State	Resets the device to its original state. This may include (if applicable): reset graphic rendition, clear tabulation stops, reset to default font, and more.

Pressing special keys on the keyboard, as well as outputting many xterm CSI, DCS, or OSC sequences, often produces a CSI, DCS, or OSC sequence, sent from the terminal to the computer as though the user typed it.

CSI sequences

The ESC [is followed by any number (including none) of "parameter bytes" in the range 0x30–0x3F (ASCII 0–9; <=>?), then by any number of "intermediate bytes" in the range 0x20–0x2F (ASCII space and !"#\$%&'()*+,-./), then finally by a single "final byte" in the range 0x40–0x7E (ASCII @–Z[\]^_`a–z{ | }~).^{[18]:5.4}

All common sequences just use the parameters as a series of semicolon-separated numbers such as 1;2;3. Missing numbers are treated as 0 (1;;3 acts like the middle number is 0, and no parameters at all in ESC [m acts like a 0 reset code). Some sequences (such as CUU) treat 0 as 1 in order to make missing parameters useful.^{[18]:F.4.2} Bytes other than digits and semicolon seem to not be used.

A subset of arrangements was declared "private" so that terminal manufacturers could insert their own sequences without conflicting with the standard. Sequences containing the parameter bytes <=>? or the final bytes 0x70–0x7E (p–z{ | }~) are private.

The behavior of the terminal is undefined in the case where a CSI sequence contains any character outside of the range 0x20–0x7E. These illegal characters are either Co control characters (the range 0–0x1F), DEL (0x7F), or bytes with the high bit set. Possible responses are to ignore the byte, to process it immediately, and furthermore whether to continue with the CSI sequence, to abort it immediately, or to ignore the rest of it.

Some ANSI control sequences (not a complete list)

Code	Name	Effect
CSI <i>n</i> A	CUU – Cursor Up	Moves the cursor <i>n</i> (default 1) cells in the given direction. If the cursor is already at the edge of the screen, this has no effect.
CSI <i>n</i> B	CUD – Cursor Down	
CSI <i>n</i> C	CUF – Cursor Forward	
CSI <i>n</i> D	CUB – Cursor Back	
CSI <i>n</i> E	CNL – Cursor Next Line	Moves cursor to beginning of the line <i>n</i> (default 1) lines down. (not ANSI.SYS)
CSI <i>n</i> F	CPL – Cursor Previous Line	Moves cursor to beginning of the line <i>n</i> (default 1) lines up. (not ANSI.SYS)
CSI <i>n</i> G	CHA – Cursor Horizontal Absolute	Moves the cursor to column <i>n</i> (default 1). (not ANSI.SYS)
CSI <i>n</i> ; <i>m</i> H	CUP – Cursor Position	Moves the cursor to row <i>n</i> , column <i>m</i> . The values are 1-based, and default to 1 (top left corner) if omitted. A sequence such as CSI ;5H is a synonym for CSI 1;5H as well as CSI 17;H is the same as CSI 17H and CSI 17;1H
CSI <i>n</i> J	ED – Erase in Display	Clears part of the screen. If <i>n</i> is 0 (or missing), clear from cursor to end of screen. If <i>n</i> is 1, clear from cursor to beginning of the screen. If <i>n</i> is 2, clear entire screen (and moves cursor to upper left on DOS ANSI.SYS). If <i>n</i> is 3, clear entire screen and delete all lines saved in the scrollbar buffer (this feature was added for xterm and is supported by other terminal applications).
CSI <i>n</i> K	EL – Erase in Line	Erases part of the line. If <i>n</i> is 0 (or missing), clear from cursor to the end of the line. If <i>n</i> is 1, clear from cursor to beginning of the line. If <i>n</i> is 2, clear entire line. Cursor position does not change.
CSI <i>n</i> S	SU – Scroll Up	Scroll whole page up by <i>n</i> (default 1) lines. New lines are added at the bottom. (not ANSI.SYS)
CSI <i>n</i> T	SD – Scroll Down	Scroll whole page down by <i>n</i> (default 1) lines. New lines are added at the top. (not ANSI.SYS)
CSI <i>n</i> ; <i>m</i> f	HVP – Horizontal Vertical Position	Same as CUP
CSI <i>n</i> m	SGR – Select Graphic Rendition	Sets the appearance of the following characters, see SGR parameters below.
CSI 5i	AUX Port On	Enable aux serial port usually for local serial printer
CSI 4i	AUX Port Off	Disable aux serial port usually for local serial printer
CSI 6n	DSR – Device Status Report	Reports the cursor position (CPR) to the application as (as though typed at the keyboard) ESC [<i>n</i> ; <i>m</i> R, where <i>n</i> is the row and <i>m</i> is the column.)
CSI s	SCP – Save Cursor Position	Saves the cursor position/state.
CSI u	RCP – Restore Cursor Position	Restores the cursor position/state.

Some popular private sequences

Code	Effect
CSI ? 25 h	DECTCEM Shows the cursor, from the VT320 .
CSI ? 25 l	DECTCEM Hides the cursor.
CSI ? 1049 h	Enable alternative screen buffer
CSI ? 1049 l	Disable alternative screen buffer
CSI ? 2004 h	Turn on bracketed paste mode . Text pasted into the terminal will be surrounded by ESC [200~ and ESC [201~, and characters in it should not be treated as commands (for example in Vim). ^[20] From Unix terminal emulators.
CSI ? 2004 l	Turn off bracketed paste mode.

SGR (Select Graphic Rendition) parameters

SGR sets display attributes. Several attributes can be set in the same sequence, separated by semicolons.^[21] Each display attribute remains in effect until a following occurrence of SGR resets it.^[1] If no codes are given, CSI *m* is treated as CSI 0 *m* (reset / normal).

In ECMA-48 SGR is called "Select Graphic Rendition".^[1] In Linux manual pages the term "Set Graphics Rendition" is used.^[21]

Code	Effect	Note
0	Reset / Normal	all attributes off
1	Bold or increased intensity	
2	Faint (decreased intensity)	
3	Italic	Not widely supported. Sometimes treated as inverse.
4	Underline	
5	Slow Blink	less than 150 per minute
6	Rapid Blink	MS-DOS ANSI.SYS; 150+ per minute; not widely supported
7	<u>reverse video</u>	swap foreground and background colors
8	Conceal	Not widely supported.
9	Crossed-out	Characters legible, but marked for deletion.
10	Primary(default) font	
11–19	Alternative font	Select alternative font <i>n</i> – 10
20	<u>Fraktur</u>	Rarely supported
21	Doubly underline or Bold off	Double-underline per ECMA-48. ^[22] <i>See discussion</i>
22	Normal color or intensity	Neither bold nor faint
23	Not italic, not Fraktur	
24	Underline off	Not singly or doubly underlined
25	Blink off	
27	Inverse off	
28	Reveal	conceal off
29	Not crossed out	
30–37	Set foreground color	See color table below
38	Set foreground color	Next arguments are 5; n or 2; r; g; b, see below
39	Default foreground color	implementation defined (according to standard)
40–47	Set background color	See color table below
48	Set background color	Next arguments are 5; n or 2; r; g; b, see below
49	Default background color	implementation defined (according to standard)
51	Framed	
52	Encircled	
53	Overlined	
54	Not framed or encircled	
55	Not overlined	
60	ideogram underline or right side line	Rarely supported
61	ideogram double underline or double line on the right side	
62	ideogram overline or left side line	
63	ideogram double overline or double line on the left side	
64	ideogram stress marking	
65	ideogram attributes off	reset the effects of all of 60–64
90–97	Set bright foreground color	aixterm (not in standard)
100–107	Set bright background color	aixterm (not in standard)

Colors

3/4 bit

The original specification only had 8 colors, and just gave them names. The SGR parameters 30-37 selected the foreground color, while 40-47 selected the background. Quite a few terminals implemented "bold" (SGR code 1) as a brighter color rather than a different font, thus providing 8 additional foreground colors. Usually you could not get these as background colors, though sometimes inverse video (SGR code 7) would allow that. Examples: to get black letters on white background use ESC [30;47m, to get

red use ESC[31m, to get bright red use ESC[1;31m. To reset colors to their defaults, use ESC[39;49m (not supported on some terminals), or reset all attributes with ESC[0m. Later terminals added the ability to directly specify the "bright" colors with 90-97 and 100-107.

When hardware started using 8-bit DACs several pieces of software assigned 24-bit color numbers to these names. The chart below shows values sent to the DAC for some common hardware and software.

Name	FG Code	BG Code	VGA ^[nb 2]	Windows Console ^[nb 3]	PowerShell	Terminal.app	PuTTY	mIRC	xterm	x ^[nb 4]	Ubuntu ^[nb 5]
Black	30	40	0,0,0								1,1,1
Red	31	41	170,0,0	128,0,0	128,0,0	194,54,33	187,0,0	127,0,0	205,0,0	255,0,0	222,56,43
Green	32	42	0,170,0	0,128,0	0,128,0	37,188,36	0,187,0	0,147,0	0,205,0	0,255,0	57,181,74
Yellow	33	43	170,85,0 ^[nb 6]	128,128,0	238,237,240	173,173,39	187,187,0	252,127,0	205,205,0	255,255,0	255,199,6
Blue	34	44	0,0,170	0,0,128	0,0,128	73,46,225	0,0,187	0,0,127	0,0,238 ^[23]	0,0,255	0,111,184
Magenta	35	45	170,0,170	128,0,128	1,36,86	211,56,211	187,0,187	156,0,156	205,0,205	255,0,255	118,38,113
Cyan	36	46	0,170,170	0,128,128	0,128,128	51,187,200	0,187,187	0,147,147	0,205,205	0,255,255	44,181,233
White	37	47	170,170,170	192,192,192	192,192,192	203,204,205	187,187,187	210,210,210	229,229,229	255,255,255	204,204,204
Bright Black	90	100	85,85,85	128,128,128	128,128,128	129,131,131	85,85,85	127,127,127	127,127,127		128,128,128
Bright Red	91	101	255,85,85	255,0,0	255,0,0	252,57,31	255,85,85	255,0,0	255,0,0		255,0,0
Bright Green	92	102	85,255,85	0,255,0	0,255,0	49,231,34	85,255,85	0,252,0	0,255,0	144,238,144	0,255,0
Bright Yellow	93	103	255,255,85	255,255,0	255,255,0	234,236,35	255,255,85	255,255,0	255,255,0	255,255,224	255,255,0
Bright Blue	94	104	85,85,255	0,0,255	0,0,255	88,51,255	85,85,255	0,0,252	92,92,255 ^[24]	173,216,230	0,0,255
Bright Magenta	95	105	255,85,255	255,0,255	255,0,255	249,53,248	255,85,255	255,0,255	255,0,255		255,0,255
Bright Cyan	96	106	85,255,255	0,255,255	0,255,255	20,240,240	85,255,255	0,255,255	0,255,255	224,255,255	0,255,255
Bright White	97	107	255,255,255	255,255,255	255,255,255	233,235,235	255,255,255	255,255,255	255,255,255		255,255,255

8-bit

As 256-color lookup tables became common on graphic cards, escape sequences were added to select from a pre-defined set of 256 colors:

```

ESC[ 38;5;<n> m Select foreground color
ESC[ 48;5;<n> m Select background color
  0- 7: standard colors (as in ESC [ 30-37 m)
  8- 15: high intensity colors (as in ESC [ 90-97 m)
 16-231: 6 × 6 × 6 cube (216 colors): 16 + 36 × r + 6 × g + b (0 ≤ r, g, b ≤ 5)
 232-255: grayscale from black to white in 24 steps
    
```

The ITU's T.416 Information technology - Open Document Architecture (ODA) and interchange format: Character content architectures^[25] uses ':' as separator characters instead:

```

ESC[ 38:5:<n> m Select foreground color
ESC[ 48:5:<n> m Select background color
    
```

256-color mode — foreground: ESC[38;5;#m background: ESC[48;5;#m																																			
Standard colors							High-intensity colors																												
0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15																				
216 colors																																			
16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51
52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87
88	89	90	91	92	93	94	95	96	97	98	99	100	101	102	103	104	105	106	107	108	109	110	111	112	113	114	115	116	117	118	119	120	121	122	123
124	125	126	127	128	129	130	131	132	133	134	135	136	137	138	139	140	141	142	143	144	145	146	147	148	149	150	151	152	153	154	155	156	157	158	159
160	161	162	163	164	165	166	167	168	169	170	171	172	173	174	175	176	177	178	179	180	181	182	183	184	185	186	187	188	189	190	191	192	193	194	195
196	197	198	199	200	201	202	203	204	205	206	207	208	209	210	211	212	213	214	215	216	217	218	219	220	221	222	223	224	225	226	227	228	229	230	231
Grayscale colors																																			
232	233	234	235	236	237	238	239	240	241	242	243	244	245	246	247	248	249	250	251	252	253	254	255												

24-bit

As "true color" graphic cards with 16 to 24 bits of color became common, Xterm,^[19] KDE's *Konsole*,^[26] as well as all libvt based terminals^[27] (including *GNOME Terminal*) support 24-bit foreground and background color setting^[28]

```
ESC[ 38;2;<r>;<g>;<b> m Select RGB foreground color
ESC[ 48;2;<r>;<g>;<b> m Select RGB background color
```

The ITU's T.416 Information technology - Open Document Architecture (ODA) and interchange format: Character content architectures^[25] which was adopted as ISO/IEC International Standard 8613-6 gives an alternative version that seems to be less supported:

```
ESC[ 38:2:<Color-Space-ID>;<r>;<g>;<b>;<unused>;<CS tolerance>;<Color-Space: 0="CIELUV"; 1="CIELAB">; m Select RGB foreground color
ESC[ 48:2:<Color-Space-ID>;<r>;<g>;<b>;<unused>;<CS tolerance>;<Color-Space: 0="CIELUV"; 1="CIELAB">; m Select RGB background color
```

Note that this uses the otherwise reserved '.' character to separate the sub-options which may have been a source of confusion for real-world implementations. It also documents using '3' as the second parameter to specify colors using a Cyan-Magenta-Yellow scheme and '4' for a Cyan-Magenta-Yellow-Black one, the latter using the position marked as "unused" in the above examples for the Black component.

Also note that many implementation that recognize '.' as the separator erroneously forget about the color space identifier parameter and hence shift the position of the remaining ones.

Examples

CSI 2 J — This clears the screen and, on some devices, locates the cursor to the y,x position 1,1 (upper left corner).

CSI 32 m — This makes text green. The green may be a dark, dull green, so you may wish to enable Bold with the sequence CSI 1 m which would make it bright green, or combined as CSI 32 ; 1 m. Some implementations use the Bold state to make the character Bright.

CSI 0 ; 6 8 ; "DIR" ; 13 p — This reassigns the key F10 to send to the keyboard buffer the string "DIR" and ENTER, which in the DOS command line would display the contents of the current directory. (MS-DOS ANSI.SYS only) This was sometimes used for *ANSI bombs*. This is a private-use code (as indicated by the letter p), using a non-standard extension to include a string-valued parameter. Following the letter of the standard would consider the sequence to end at the letter D.

CSI s — This saves the cursor position. Using the sequence CSI u will restore it to the position. Say the current cursor position is 7(y) and 10(x). The sequence CSI s will save those two numbers. Now you can move to a different cursor position, such as 20(y) and 3(x), using the sequence CSI 20 ; 3 H or CSI 20 ; 3 f. Now if you use the sequence CSI u the cursor position will return to 7(y) and 10(x). Some terminals require the DEC sequences ESC 7 / ESC 8 instead which is more widely supported.

Example of use in shell scripting

ANSI escape codes are often used in *UNIX* and UNIX-like *terminals* to provide *syntax highlighting*. For example, on compatible terminals, the following *list* command color-codes file and directory names by type.

```
ls --color
```

Users can employ escape codes in their scripts by including them as part of *standard output* or *standard error*. For example, the following GNU *sed* command embellishes the output of the *make* command by displaying lines containing words starting with "WARN" in *reverse video* and words starting with "ERR" in bright yellow on a dark red background (letter case is ignored). The representations of the codes are highlighted.^[29]

```
make 2>&1 | sed -e 's/.*\bWARN.*/\x1b[7m&\x1b[0m/i' -e 's/.*\bERR.*/\x1b[93;41m&\x1b[0m/i'
```

The following *Bash* function flashes the terminal (by alternately sending reverse and normal video mode codes) until the user presses a key.^[30]

```
flasher () { while true; do printf \e[?5h; sleep 0.1; printf \e[?5l; read -s -n1 -t1 && break; done; }
```

This can be used to alert a programmer when a lengthy command terminates, such as with `make ; flasher`.^[31]

```
printf \033c
```

This will reset the console, similar to the command `reset` on modern Linux systems; however it should work even on older Linux systems and on other (non-Linux) UNIX variants.

Invalid and ambiguous sequences in use

- The Linux console uses OSC P n rr gg bb to change the palette, which, if hard-coded into an application, may hang other terminals. However, appending ST will be ignored by Linux and form a proper, ignorable sequence for other terminals.
- On the Linux console, certain function keys generate sequences of the form CSI [*char*. The CSI sequence should terminate on the [.
- Old versions of *Terminator* generate SS3 1; *modifiers char* when F1–F4 are pressed with modifiers. The faulty behavior was copied from *GNOME Terminal*.
- xterm replies CSI *row* ; *column* R if asked for cursor position and CSI 1 ; *modifiers* R if the F3 key is pressed with modifiers, which collide in the case of `row == 1`. This can be avoided by using the ? private modifier, which will be reflected in the response.
- many terminals prepend ESC to any character that is typed with the alt key down. This creates ambiguity for uppercase letters and symbols @/]^_, which would form C1 codes.

- [Konsole](#) generates *SS3 modifiers char* when F1–F4 are pressed with modifiers.

See also

- [ANSI art](#)
- [Control character](#)
- [Advanced Video Attribute Terminal Assembler and Recreator \(AVATAR\)](#)
- [ISO/IEC JTC 1/SC 2](#)
- [C0 and C1 control codes](#)

Notes

- The screen display could be replaced by drawing the entire new screen's contents at the bottom, scrolling the previous screen up sufficiently to erase all the old text. The user would see the scrolling, and the hardware [cursor](#) would be left at the very bottom. Some early [batch files](#) achieved rudimentary "full screen" displays in this way.
- Typical colors that are used when booting PCs and leaving them in text mode, which used a 16-entry color table. The colors are different in the EGA/VGA graphic modes.
- As of Windows XP
- Above color name from X11 rgb.txt color database, with "light" prefixed for the bright colors.
- For virtual terminals, from `/etc/vtrgb`.
- On terminals based on [CGA](#) compatible hardware, such as ANSI.SYS running on DOS, this normal intensity foreground color is rendered as Orange. CGA [RGBI](#) monitors contained hardware to modify the dark yellow color to an orange/brown color by reducing the green component. See this [ansi art](#) (<http://sixteencolors.net/pack/ciapak26/DH-JNS11.CIA>) Archived (<https://web.archive.org/web/20110725014401/http://sixteencolors.net/pack/ciapak26/DH-JNS11.CIA>) 25 July 2011 at the [Wayback Machine](#) as an example.

References

- ↑ "Standard ECMA-48: Control Functions for Character-Imaging I/O Devices" (<http://www.ecma-international.org/publications/files/ECMA-ST/ECMA-48,%202nd%20Edition,%20August%201979.pdf>) (PDF) (Second ed.). Ecma International. August 1979.
- ↑ Williams, Paul (2006). "Digital's Video Terminals" (https://vt100.net/dec/vt_history). VT100.net. Retrieved 2011-08-17.
- ↑ Heathkit Company (1979). "Heathkit Catalog 1979" (https://web.archive.org/web/20120113230301/http://www.pestingers.net/Computer_history/Computers_79.htm). Heathkit Company. Archived from the original (http://www.pestingers.net/Computer_history/Computers_79.htm) on 2012-01-13. Retrieved 2011-11-04.
- ↑ "Withdrawn FIPS Listed by Number" (https://www.nist.gov/sites/default/files/documents/2016/12/15/withdrawn_fips_by_numerical_order_index.pdf) (PDF). *National Institute of Standards and Technology*. December 15, 2016.
- ↑ Mefford, Michael (1989-02-07). "ANSI.com: Download It Here" (<https://www.pcmag.com/article2/0,2817,5343,00.asp>). *PC Magazine*. Retrieved 2011-08-10.
- ↑ Kegel, Dan; Auer, Eric (1999-02-28). "Nansi and NNansi – ANSI Drivers for MS-DOS" (<http://www.kegel.com/nansi/>). Dan Kegel's Web Hostel. Retrieved 2011-08-10.
- ↑ "PTS-DOS 2000 Pro User Manual" (http://download.paragon-software.com/doc/manual_dos_eng.pdf) (PDF). Buggingen, Germany: Paragon Technology GmbH. 1999. Archived (https://web.archive.org/web/20180512094512/http://download.paragon-software.com/doc/manual_dos_eng.pdf) (PDF) from the original on 2018-05-12. Retrieved 2018-05-12.
- ↑ Günther, Jens; Ernst, Tobias (2004-04-25) [1996]. Ellsäßer, Wolfgang, ed. "Inoffizielle deutschsprachige PTS-DOS-FAQ (PTS/FAQD)" (https://almnet.de/ptsdos/ptsfaq_d.html#absIV1) [Inofficial German PTS-DOS FAQ] (in German). Retrieved 2018-10-02.
- ↑ *CCI Multiuser DOS 7.22 GOLD Online Documentation*. Concurrent Controls, Inc. (CCI). 1997-02-10. HELP.HLP.
- ↑ "Using C-Kermit" (<https://books.google.com/books?id=Z0ejBQAAQBAJ&pg=PA88>), p. 88.
- ↑ "Amiga Printer Command Definitions" (http://wiki.amigaos.net/wiki/Printer_Device#Printer_Command_Definitions). Commodore. Retrieved 2013-07-10.
- ↑ Hood, Jason (2005). "Process ANSI escape sequences for Windows console programs" (<https://github.com/adoxa/ansicon>). Jason Hood's Home page. Retrieved 2013-05-09.
- ↑ "colorama 0.2.5 :" (<https://pypi.python.org/pypi/colorama>). *Python Package Index*. Retrieved 2013-08-17.
- ↑ bitcrazed. "Console Virtual Terminal Sequences - Windows Console" (<https://docs.microsoft.com/en-us/windows/console/console-virtual-terminal-sequences>). *docs.microsoft.com*. Retrieved 2018-05-30.
- ↑ "Windows 10 Creators Update: What's new in Bash/WSL & Windows Console" (<https://blogs.msdn.microsoft.com/commandline/2017/04/11/windows-10-creators-update-whats-new-in-bashwsl-windows-console/#comment-13325>). Comment by ulrichb and reply by Rick Turner.
- ↑ Grehan, Oisín (2016-02-04). "Windows 10 TH2 (v1511) Console Host Enhancements" ([http://www.nivot.org/blog/post/2016/02/04/Windows-10-TH2-\(v1511\)-Console-Host-Enhancements](http://www.nivot.org/blog/post/2016/02/04/Windows-10-TH2-(v1511)-Console-Host-Enhancements)). Retrieved 2016-02-10.
- ↑ "PowerShell Help: About Special Characters" (https://docs.microsoft.com/en-us/powershell/module/microsoft.powershell.core/about/about_special_characters?view=powershell-6).
- ↑ "Standard ECMA-48: Control Functions for Coded Character Sets" (<http://www.ecma-international.org/publications/standards/Ecma-048.htm>) (Fifth ed.). Ecma International. June 1991.
- ↑ "XTerm Control Sequences" (<http://invisible-island.net/xterm/ctlseqs/ctlseqs.html>). *invisible-island.net*. 2014-01-13. Retrieved 2014-04-13.
- ↑ Conrad Irwin (April 2013). "bracketed paste mode" (<https://cirw.in/blog/bracketed-paste>). *cirw.in*.
- ↑ "console_codes(4) - Linux manual page" (http://man7.org/linux/man-pages/man4/console_codes.4.html). *man7.org*. Retrieved 2018-03-23.
- ↑ ECMA International. "Control Functions for Coded Character Sets" (<http://www.ecma-international.org/publications/files/ECMA-ST/Ecma-048.pdf>) (PDF). p. 61 on printed page, PDF page 75.
- ↑ Changed from 0,0,205 in July 2004 "Patch #192 – 2004/7/12 – XFree86 4.4.99.9" (http://invisible-island.net/xterm/xterm.log.html#xterm_192).
- ↑ Changed from 0,0,255 in July 2004 "Patch #192 – 2004/7/12 – XFree86 4.4.99.9" (http://invisible-island.net/xterm/xterm.log.html#xterm_192).
- ↑ "IT 140 Information Technology Open Document Architecture (ODA) and Interchange Format: Character content architecture" (<http://www.it-europe.org/standards/it140>). Retrieved 2018-03-23.

25. [ITU-T Recommendation T.416 \(03/93\) Information technology – Open Document Architecture \(ODA\) and interchange format: Character content architectures](https://www.itu.int/rec/dologin_pub.asp?lang=e&id=T-REC-T.416-199303-!!PDF-E&type=items) (https://www.itu.int/rec/dologin_pub.asp?lang=e&id=T-REC-T.416-199303-!!PDF-E&type=items).
26. ["color-spaces.pl \(a copy of 256colors2.pl from xterm dated 1999-07-11\)"](https://quickgit.kde.org/?p=konsole.git&a=blob&f=tests%2Fcolor-spaces.pl) (<https://quickgit.kde.org/?p=konsole.git&a=blob&f=tests%2Fcolor-spaces.pl>). KDE. 2006-12-06.
27. ["libvte's bug report and patches"](https://bugzilla.gnome.org/show_bug.cgi?id=704449) (https://bugzilla.gnome.org/show_bug.cgi?id=704449). GNOME Bugzilla. 2014-04-04. Retrieved 2016-06-05.
28. ["README.moreColors"](https://cgit.kde.org/konsole.git/tree/doc/user/README.moreColors) (<https://cgit.kde.org/konsole.git/tree/doc/user/README.moreColors>). KDE. 2010-04-22.
29. ["Chapter 9. System tips"](http://www.debian.org/doc/manuals/debian-reference/ch09.en.html#_colorized_shell_echo) (http://www.debian.org/doc/manuals/debian-reference/ch09.en.html#_colorized_shell_echo). *debian.org*.
30. ["VT100.net: Digital VT100 User Guide"](http://vt100.net/docs/vt100-ug/chapter3.html) (<http://vt100.net/docs/vt100-ug/chapter3.html>). Retrieved 2015-01-19.
31. ["bash – How to get a notification when my commands are done – Ask Different"](http://apple.stackexchange.com/questions/9412/how-to-get-a-notification-when-my-commands-are-done) (<http://apple.stackexchange.com/questions/9412/how-to-get-a-notification-when-my-commands-are-done>). Retrieved 2015-01-19.

External links

- [Standard ECMA-48, Control Functions For Coded Character Sets](http://www.ecma-international.org/publications/standards/Ecma-048.htm) (<http://www.ecma-international.org/publications/standards/Ecma-048.htm>). (*5th edition, June 1991*), European Computer Manufacturers Association, Geneva 1991 (also published by ISO and IEC as standard ISO/IEC 6429)
- [vt100.net DEC Documents](http://vt100.net/docs/) (<http://vt100.net/docs/>)
- [ANSI.SYS -- ansi terminal emulation escape sequences](https://web.archive.org/web/20060206022229/http://enterprise.aacc.cc.md.us/~rhs/ansi.html) (<https://web.archive.org/web/20060206022229/http://enterprise.aacc.cc.md.us/~rhs/ansi.html>) at the [Wayback Machine](#) (archived 6 February 2006)
- [Xterm / Escape Sequences](http://invisible-island.net/xterm/ctlseqs/ctlseqs.html) (<http://invisible-island.net/xterm/ctlseqs/ctlseqs.html>)
- [AIXterm / Escape Sequences](http://publib.boulder.ibm.com/infocenter/aix/v6r1/index.jsp?topic=%2Fcom.ibm.aix.cmds%2Fdoc%2Faixcmds1%2Faixterm.htm) (<http://publib.boulder.ibm.com/infocenter/aix/v6r1/index.jsp?topic=%2Fcom.ibm.aix.cmds%2Fdoc%2Faixcmds1%2Faixterm.htm>)
- [A collection of escape sequences for terminals that are vaguely compliant with ECMA-48 and friends.](http://bjh21.me.uk/all-escapes/all-escapes.txt) (<http://bjh21.me.uk/all-escapes/all-escapes.txt>)
- [ANSI Escape Sequences](http://ascii-table.com/ansi-escape-sequences.php) (<http://ascii-table.com/ansi-escape-sequences.php>)
- [ITU-T Rec. T.416 \(03/93\) Information technology – Open Document Architecture \(ODA\) and interchange format: Character content architectures](https://www.itu.int/rec/dologin_pub.asp?lang=e&id=T-REC-T.416-199303-!!PDF-E&type=items) (https://www.itu.int/rec/dologin_pub.asp?lang=e&id=T-REC-T.416-199303-!!PDF-E&type=items)

Retrieved from "https://en.wikipedia.org/w/index.php?title=ANSI_escape_code&oldid=876599490"

This page was last edited on 3 January 2019, at 08:33 (UTC).

Text is available under the [Creative Commons Attribution-ShareAlike License](#); additional terms may apply. By using this site, you agree to the [Terms of Use](#) and [Privacy Policy](#). Wikipedia® is a registered trademark of the [Wikimedia Foundation, Inc.](#), a non-profit organization.